

AMENDMENTS TO THE CLAIMS

The following is a complete listing of the pending claims with a status identifier in parenthesis.

LISTING OF CLAIMS

1. (Cancelled)
2. (Currently Amended) The display device according to claim [[1]] 5, wherein the output buffer comprises:
 - a plurality of transistors, connected in parallel, for outputting the analog voltage; and
 - a switching circuit for switching at least one of the plurality of transistors between an operative state and an inoperative state; wherein the bias current control portion changes the bias current by changing the number of said plurality of transistors that are in the operative state with the switching circuit.
3. (Currently Amended) The display device according to claim [[1]] 5, wherein the output buffer comprises:
 - a transistor for outputting the analog voltage; and
 - an operating point changing circuit for changing an operating point of the transistor;wherein the bias current control portion changes the bias current by changing the operation point of the transistor with the operating point changing circuit.
4. (Cancelled)
5. (Currently Amended) ~~The display device according to claim 1;~~ A display device which includes a display portion having a capacitive load and an output buffer having a driving capability that depends on a bias current, and which displays an image on the display portion by letting the output buffer apply an analog voltage corresponding to an input image signal to the capacitive load to drive the display portion, the display device comprising:
 - a bias current control portion that controls the bias current;
 - wherein the output buffer is configured such that the bias current can be dynamically changed;

wherein the bias current control portion changes the bias current while the display portion is driven; and

wherein the bias current control portion controls the bias current such that, after a predetermined time within the charge period or the discharge period, the bias current is smaller than at the beginning of the charge period or the discharge period.

6. (Currently Amended) ~~The display device according to claim 1,~~ A display device which includes a display portion having a capacitive load and an output buffer having a driving capability that depends on a bias current, and which displays an image on the display portion by letting the output buffer apply an analog voltage corresponding to an input image signal to the capacitive load to drive the display portion, the display device comprising:

a bias current control portion that controls the bias current;

wherein the output buffer is configured such that the bias current can be dynamically changed;

wherein the bias current control portion changes the bias current while the display portion is driven; and

wherein the bias current control portion determines, based on the input image signal, a time within the charge period or the discharge period at which the bias current is to be reduced, and controls the bias current such that, after that determined time, the bias current is smaller than at the beginning of the charge period or the discharge period.

7. (Currently Amended) ~~The display device according to claim 1,~~ A display device which includes a display portion having a capacitive load and an output buffer having a driving capability that depends on a bias current, and which displays an image on the display portion by letting the output buffer apply an analog voltage corresponding to an input image signal to the capacitive load to drive the display portion, the display device comprising:

a bias current control portion that controls the bias current;

wherein the output buffer is configured such that the bias current can be dynamically changed;

wherein the bias current control portion changes the bias current while the display portion is driven; and

wherein the bias current control portion determines, based on a charge/discharge current flowing between the output buffer and the capacitive load, a time within the charge period or the

discharge period at which the bias current is to be reduced, and controls the bias current such that, after that determined time, the bias current is smaller than at the beginning of the charge period or the discharge period.

8. (Previously Presented) The display device according to claim 5, wherein the bias current control portion completely stops the bias current after the time that has been determined as the time within the charge period or the discharge period at which the bias current is to be reduced.

9 – 12. (Cancelled)

13. (Currently Amended) ~~The driving method according to claim 11,~~ A driving method for driving a display portion including a capacitive load, in order to display an image on the display portion, by applying an analog voltage corresponding to an input image signal to the capacitive load with an output buffer that has a driving ability that depends on a bias current, the driving method comprising:

a bias current changing step of changing the bias current while the display portion is driven, wherein, in the bias current changing step, the bias current is changed such that, after a predetermined time within the charge period or the discharge period, the bias current is smaller than at the beginning of the charge period or the discharge period.

14. (Currently Amended) ~~The driving method according to claim 11,~~ A driving method for driving a display portion including a capacitive load, in order to display an image on the display portion, by applying an analog voltage corresponding to an input image signal to the capacitive load with an output buffer that has a driving ability that depends on a bias current, the driving method comprising:

a bias current changing step of changing the bias current while the display portion is driven; and

~~further comprising~~ a time determination step of determining, based on the input image signal, a time within the charge period or the discharge period at which the bias current is to be reduced; and wherein in the bias current changing step, the bias current is changed such that, after that determined time within the charge period or the discharge period, the bias current is smaller than at the beginning of the charge period or the discharge period.

15. (Currently Amended) ~~The driving method according to claim 11, further comprising~~
A driving method for driving a display portion including a capacitive load, in order to display an image on the display portion, by applying an analog voltage corresponding to an input image signal to the capacitive load with an output buffer that has a driving ability that depends on a bias current, the driving method comprising:

a bias current changing step of changing the bias current while the display portion is driven; and

a time determination step of determining, based on a charge/discharge current flowing between the output buffer and the capacitive load, a time within the charge period or the discharge period at which the bias current is to be reduced; and

wherein in the bias current changing step, the bias current is changed such that, after that determined time within the charge period or the discharge period, the bias current is smaller than at the beginning of the charge period or the discharge period.

16. (Previously Presented) The driving method according to claim 13, wherein in the bias current changing step, the bias current is completely stopped after the time that has been determined as the time within the charge period or the discharge period at which the bias current is to be reduced.

17. (Previously Presented) The display device according to claim 6, wherein the bias current control portion completely stops the bias current after the time that has been determined as the time within the charge period or the discharge period at which the bias current is to be reduced.

18. (Previously Presented) The display device according to claim 7, wherein the bias current control portion completely stops the bias current after the time that has been determined as the time within the charge period or the discharge period at which the bias current is to be reduced.

19. (Previously Presented) The driving method according to claim 14, wherein in the bias current changing step, the bias current is completely stopped after the time that has been

determined as the time within the charge period or the discharge period at which the bias current is to be reduced.

20. (Previously Presented) The driving method according to claim 15, wherein in the bias current changing step, the bias current is completely stopped after the time that has been determined as the time within the charge period or the discharge period at which the bias current is to be reduced.